

marantz®

NR1607

ULTRA-SLIM 7.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND BUILT-IN WI-FI



A thrilling new dimension in surround sound from a high-quality AV receiver occupying minimal space: that's the promise of the NR1607, which features Dolby Atmos immersive surround decoding to deliver breathtaking surround sound from today's advanced movie soundtracks. Slim enough to slip into any TV cabinet, it delivers the same revolutionary Dolby Atmos 3D surround sound found in the very best cinemas, creating an overhead surround soundfield to give a dramatic expansion of the sonic space. A future firmware update will also allow the NR1607 to decode DTS:X soundtracks, for ultimate compatibility with this new world of 3D sound. And the NR1607 is ready for Ultra High Definition vision, too: its advanced video section is fully compatible with the latest HDMI 2.0a and HDCP 2.2 specifications on all 8 HDMI inputs, allowing it to pass all the latest video formats to an Ultra HD TV or projector. Wi-Fi and Bluetooth, with dual antennas for robust connection, let you stream your music via AirPlay or Spotify Connect, or from local network storage drives – all the way through to high resolution audio, and with the famous Marantz sound quality. And it's easy to control, too: the free "Marantz 2016 AVR Remote" app is available from the Apple app store, Google Play, and the Amazon appstore, to let you control the receiver from your smartphone or tablet.

Highlights

Your Benefits

Slim Design 7.2 channel AV Receiver with 90W per channel	Enough power to fill medium size rooms from a small cabinet with renowned Marantz sound
Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	Improved network stability especially in WiFi-crowded homes
4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support	Plenty of inputs for your Blu-ray Player, game console and more
Analogue to HDMI conversion and SD/HD to 4K Upscaling for legacy video sources	Full HD and even Ultra HD video quality from existing DVDs or analogue sources
Dolby Atmos (up to 5.1.2) and DTS:X (via firmware update)	Immersive 3D sound with effects from overhead
AirPlay, Bluetooth, Internet Radio, Spotify Connect, Network Audio Streaming	Access to almost unlimited online music sources
DSD (2.8/5.6MHz), FLAC, ALAC, AIFF and WAV support	High Resolution audio streaming, even gapless
Audyssey MultEQ, Dynamic Volume and Dynamic EQ	Delivering perfect equalization for your individual room
Colour-coded speaker terminals, Setup Assistant, Marantz 2016 AVR Remote App	Hassle-free installation, setup and operation
Intelligent ECO mode with off/on/auto setting	Energy-conscious without compromising on performance

www.marantz.eu



because music matters

NR1607

ULTRA-SLIM 7.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND BUILT-IN WI-FI



Design and specifications are subject to change by Marantz without notice.

FEATURES	NR1607
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / Firmware update
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
NETWORK / SOURCES	
Network Audio Streaming	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (vTuner)	•
Spotify Connect *	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
FM / AM Tuner	• / •
Bluetooth	•
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 30/25/24Hz
INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 1
AUDIO	

Analogue In / Out	3 / 0	
Digital Optical In	1	
Digital Coaxial In	1	
Multichannel Pre Out	• (2.2)	
Zone audio preout	•	
Subwoofer Out	2	
SPECIFICATIONS		
Number of poweramps	7	
Power Output per channel		
6 ohm, 1 kHz, 1%, 1ch Drive	90 W	
6 ohm, 1 kHz, 0.7%, 2ch Drive	70 W	
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	50 W	
Audio Signal to Noise Ratio	98 dB	
GENERAL		
Available colours: Black / Silver-Gold	• / •	
System Remote Control	RC024SR	
Power Consumption in W	250	
Power Consumption No-Sound (ECO ...on/off) in W	30 / 40	
Standby Consumption in W	0.2 (with CEC 0.5)	
Maximum Dimensions (W x D x H) in mm	440 x 376 x 105	
Weight in kg	8.3	
EAN		
EU		
NR1607/N1B	4951035058251	Black
NR1607/N1SG	4951035058268	Silver-Gold
UK		
NR1607/T1B	4951035058251	Black
NR1607/T1SG	4951035058268	Silver-Gold

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* This feature is not available in all countries.

* All specs can be subject to change.