

Model Name	X5	X7	Model Name	X5	X7
Backlight					
Display Area	LED 1209.6 x 680.4mm	LED	Storage Temperature/Humidity	-10° - 50° / 10% - 90% 0° - 40° / 10% - 90%	
Active Screen Size	55"	1,539 x 866 mm	Working Temperature/Humidity	Wall-mounted / Floor Stand	
		70"	Mounting (optional)	,	
Display Ratio Resolution	16 : 9	16 : 9	Outline Dimension	1,320 x 886 x 87mm	1,589 x 1,049 x 78mm
	1,920 x 1,080 Pixel	1,920 x 1,080 Pixel	Packing Dimension	1,470x995x265mm	1,720 x 1,180 x 270mm
Display Colors	8 bit	10 bit	Net Weight	36Kg	65 kg
Brightness	370cd/m2	350 cd/m2	Gross Weight	45Kg	75 kg
Contrast	4000:1	4000:1		Ports	
Response Time	8 ms	6 ms	Front Interface Inputs	Microphone(3.5mm) x 1, HDMI x 1, USB(Touch) x 1, USB(Internal PC) x 1, USB(Android) x 1	
Life time	30,000Hrs	50,000 hours	Trone meriace inputs		
Consiliant	Spea			HDMI (MHI *) x 1	HDMI (MHL*) x 1
Speaker position	Forward	Forward	AV Inputs	HDMI(MHL) x 1, VGA x 1, USB (Touch) x 2, Audio (3.5mm) x 1	( *available on March, 2016), VGA x 1, USB (Touch) x 2, Audio (3.5mm) x 1
Rated Impedance	8Ω	8Ω			
Freq. Response	80Hz (±20%) -18kHz	90Hz (±20%) -18kHz	AV Outputs	3.5mm Line out x 1, HDMI x 1(Only video)	
Output S.P.L.	82±3dB	84±3dB	Othor	USB2.0 x 2, RS232 x 1, RJ45 x 1, USB3.0 x 1, SD Card Reader, OPS Slot	
Max. Power Output	2 x 15Watts	2 x 15Watts	Other		
-	Microphone Array		Other Features		
Sensitivity	-28dB±3 dB		Intelligent light detector	Yes	
Frequency Response	100 Hz - 7.75 KHz		Intelligent thermo protector	Yes	
Polar Patterns	Omnidirectional		Temperature & humidity Sensor	Yes	
Total Harmonic Distortion	<1% at 6dB SPL		Build in Wi-Fi	Yes	
Pickup range	8 meters			System	
Quantity	1 Array (4 Microphones)			ARM Cortex A9 Quad Core 1.5 GHz	
	Cameras		Chips		
Position	Top x 1, Bottom x 1(One at a time)		RAM	2GB	
Sensor	2 Mega		ROM	8GB	
View Angle	86°		Mulaino dia Fila Fannasa Compani	Support all major types of multi-media files	
Video Resolution	1,920 x 1,080 @30 fps (Max)				
Frame Rate	30 fps / 60 fps		Multimedia File Formats Support		
Electrical Electrical					
Power Consumption	Max. <160 W Standby Mode ≤0.5 W	Max. <250 W Standby Mode <0.5 W		0000	6
M. 1. M. I.		· ·		OPS P	
Working Voltage	AC 100-240V, 50/60 Hz			i5-4210M / i7-46	
Tarrel Confere	Touch		GPU	Intel HD Graphics 4600	
Touch Surface	Tempered Glass	Tempered Anti-Glare Glass	RAM	8GB DDR3	
Transparency	>89%	>90%	Hard Disk	128GB SA	
Surface Hardness	H8	H7	USB 2.0/3.0	4/	
Touch Technology	True Flat	P-/capacitive Touch	LAN	1 X 10/100	
HID support	HID	HID	HDMI Out	1	
Touch Points	10 Points in Windows / 5 Points in embedded system		Microphone in	1	
Writing Tools	Stylus or Finger	Pencil or Stylus	Line out	1	
Scan Speed	100Hz	180 Hz	SPDIF Out	1	
Positioning Accuracy	1mm	0.8 mm	Build-in Wi-Fi	802.11b/g/n	
Touch Resolutions	19,354 x 10,866	63,488 x 35,840	OS	Win8.1 x64(license not included)	

All specifications are subject to be change without further notice.



# TRUTOUCH X Series

The Next Generation of Collaboration





#### **NEWLINE INTERACTIVE**

US Headquarters
101 East Park Blvd. Suite 807
Plano, TX 75074, USA
TEL: +1-972-468-9728
Want to buy: info@newline-interactive.com
Become our partner: partner@newline-interactive.com

Europe Office
Ronda de Poniente, N´2, 1ª planta, Oficina 1B,
28760, Tres Cantos, Madrid, Spain.
TEL: +34-911169178
Want to buy: info\_eu@newline-interactive.com
Become our partner: partner\_eu@newline-interactive.com

Asia Pacific Office
4F-3, No.76,Sec.2, Jiafeng S.Rd,
Zhubei City, Hsinchu County, 30272, Taiwan
Tel: +886-3-5504768
Want to buy: info\_ap@newline-interactive.com
Become our partner: partner\_ap@newline-interactive.com



Amazing Writing Experience

Tailor-made meeting operation system

# **About Hardware**

### **TRUFLAT Design**

- \* The MOST attractive display in the world
- \* The ONLY touch screen with TRUFlat technology



## **Superb High Quality Audio**

Two speakers deliver authentic human voice, making remote conversations sound like happening in the same meeting room



## **Amazing Writing Experience**

Writing on X7 feels just like writing on your favorite notepad. Providing meeting members inspirational confidence to have better meeting





# Two 1080p Wide Angle Cameras

Switching between top and bottom cameras to make participants from multiple locations see and interact with one another naturally





#### All-in-One Design Brings Simple Installation

No complicated hardware and software installation needed. Simply turn on X7 and click to start a meeting



## Front I/O Port

Multiple I/O ports in the front make meeting member easy to access their meeting files by connecting USB drive or laptop. Special designed pen slot for keeping customized pen well stored




# **Advanced Microphone Array**

Acoustic echo cancellation, auto gain control, and noise reduction technologies enables meeting participants to be heard clearly across a 8-meter meeting room



## Connect the Way You Want

X series has multiple HDMI, USB, and AV ports, providing connections to external PC, microphone, speakers, and other multimedia players



# **About System**

#### **Start meeting**

- \* Simple interface when power on
- \* One touch to start meeting



#### Home page

- \* Four major functions Collaboration, whiteboard, sources, external storage
- \* Express keys Annotation, whiteboard, home, return, programs
- \* Timer for counting meeting time



#### Collaboration

- \* 3 frequent used collaboration meeting programs in quick start list
- \* Easily enter the same collaboration meeting program as last meeting with one touch



#### Whiteboard


- \* Single touch turns screen
- \* Natural way to share ideas and comments with meeting members
- \* Multiple colors/thickness of pen
- \* Multiple board background choices \* Multiple pages available

# **End meeting**

- \* Choose meeting notes to save to your own USB or SD card before ending meeting
- Notes and annotation will be deleted after ending meeting for information security



#### **BYOD- Bring Your Own Device**



# \* List can be customized

# Signal sources

\*Four different signal sources preview in the same screen



- \*Easy to switch between input sources
- \*Press home key to return to Android

